




**MANUAL**



**ENGLISH**

# **Galactic Beam G40 V1**



**Ordercode: 51315**

## Table of contents

---

<b>Warning</b> .....	2
Safety Instructions .....	3
Operating Determinations .....	4
Laser safety for a Class 3B Laser Product .....	5
Rigging .....	6
Connection with the mains.....	7
Return Procedure.....	7
Claims.....	7
<b>Description of the device</b> .....	8
Overview .....	8
Backside .....	9
<b>Installation</b> .....	10
<b>Set Up and Operation</b> .....	11
Control Modes.....	12
One Galactic Auto run (visual effects) .....	12
One Galactic Sound-controlled .....	12
Multiple Galactics (Master/Slave control) .....	12
Multiple Galactics (DMX Control) .....	13
Fixture Linking.....	14
Data Cabling.....	14
Control Panel.....	15
Control Mode .....	15
DMX Addressing.....	15
Menu Overview.....	16
Main Menu Options.....	17
1. Automatic / Sound-active Show .....	17
2. Automatic / Sound-active Patterns .....	17
3. Sound-active to Beam ON .....	17
4. Sound-active to Beam OFF .....	18
5. Sensitivity Mode .....	18
6. DMX Mode .....	18
7. Slave Mode.....	18
8. Reverse Setting.....	18
9. Factory default setting .....	18
DMX Channels .....	19
8 Channels .....	19
<b>Patterns</b> .....	20
<b>Maintenance</b> .....	21
Replacing a Fuse .....	21
<b>Troubleshooting</b> .....	22
No Light.....	22
No Response to DMX.....	22
<b>Product Specification</b> .....	24
<b>Dimensions</b> .....	25

## Warning



 **For your own safety, please read this user manual carefully before your initial start-up!** 



### Unpacking Instructions



Immediately upon receiving this product, carefully unpack the carton and check the contents to ensure that all parts are present, and have been received in good condition. Notify the dealer immediately and retain packing material for inspection if any parts appear damaged from shipping or the carton itself shows signs of mishandling. Save the carton and all packing materials. In the event that a fixture must be returned to the factory, it is important that the fixture be returned in the original factory box and packing.

### Your shipment includes:

- Showtec Galactic Beam G40 with IEC powercable 1,75m
- Remote plug and 2 key
- User manual



 **CAUTION! Eyedamages!!!**   
**Never look directly into the lightsource!!!**  
**Never project a single laser point!!!**

 **CAUTION!**   
**Keep this device away from rain and moisture!**  
**Unplug mains lead before opening the housing!**

## Safety Instructions

Every person involved with the installation, operation and maintenance of this device has to:

- be qualified
- follow the instructions of this manual



**CAUTION! Be careful with your operations.  
With a dangerous voltage you can suffer  
a dangerous electric shock when touching the wires!**



Before your initial start-up, please make sure that there is no damage caused by transportation. Should there be any, consult your dealer and do not use the device.

To maintain perfect condition and to ensure a safe operation, it is absolutely necessary for the user to follow the safety instructions and warning notes written in this manual.

Please consider that damages caused by manual modifications to the device are not subject to warranty.

This device contains no user-serviceable parts. Refer servicing to qualified technicians only.

## IMPORTANT:

The manufacturer will not accept liability for any resulting damages caused by the non-observance of this manual or any unauthorized modification to the device.

- Never let the power-cord come into contact with other cables! Handle the power-cord and all connections with the mains with particular caution!
- Never remove warning or informative labels from the unit.
- Never use anything to cover the ground contact.
- Never place any material over the lens.
- Never look directly into the light source.
- Never leave any cables lying around.
- Never aim the laser beam at people or animals!
- Never use the device during thunderstorms, unplug the device immediately.
- Never point a laser at aircraft, this is a federal offense.
- Never point un-terminated laser beams into the sky.
- Never open the laser housing. The high laser power levels inside of the protective housing can start fires, burn skin and will cause instant eye injury.
- Do not insert objects into air vents.
- Do not connect this device to a dimmerpack.
- Do not open the device and do not modify the device.
- Do not point lasers at highly reflective surfaces such as windows, mirrors and shiny metal. Even laser reflections can be hazardous.
- Do not expose the output optic (aperture) to cleaning chemicals
- Do not use laser if the laser appears to be emitting only one or two beams
- Do not use laser if housing is damaged or open, or if optics appear damaged in any way.
- Do not operate laser without first reading and understanding all safety and technical data in this manual. Never look into the laser aperture or laser beams
- Do not switch the device on and off in short intervals, as this would reduce the device's life.
- Do not shake the device. Avoid brute force when installing or operating the device.
- After set up and prior to public use, test laser to ensure proper function. Do not use the laser if any defect is detected. Do not use, if the laser emits only one or two laser beams rather than dozens/hundreds, as this could indicate damage to the diffraction grating optic, and could allow emission of higher laser levels.
- Only use device indoor, avoid contact with water or other liquids.
- Only operate the fixture after having checked that the housing is firmly closed and all screws are tightly fastened.
- Only operate the device after having familiarized with its functions.
- Avoid flames and do not put close to flammable liquids or gases.
- Always check the regulations when using a class IIIB laser product.

- Always check and position the laser before anybody enters the room, when the laser is facing an area with people
- Always keep case closed while operating.
- Always allow free air space of at least 50 cm around the unit for ventilation.
- Always disconnect power from the mains, when device is not used or before cleaning! Only handle the power-cord by the plug. Never pull out the plug by tugging the power-cord.
- Make sure that the device is not exposed to extreme heat, moisture or dust.
- Make sure that the available voltage is not higher than stated on the rear panel.
- Make sure that the power-cord is never crimped or damaged. Check the device and the power-cord from time to time.
- If the external cable is damaged, it has to be replaced by a qualified technician.
- If the lens is obviously damaged, it has to be replaced. So that its functions are not impaired, due to cracks or deep scratches.
- If device is dropped or struck, disconnect mains power supply immediately. Have a qualified engineer inspect for safety before operating.
- If the device has been exposed to drastic temperature fluctuation (e.g. after transportation), do not switch it on immediately. The arising condensation water might damage your device. Leave the device switched off until it has reached room temperature.
- If your Showtec device fails to work properly, discontinue use immediately. Pack the unit securely (preferably in the original packing material), and return it to your Showtec dealer for service.
- For adult use only. Device must be installed out of the reach of children. Never leave the unit running unattended.
- Never attempt to bypass the thermostatic switch or fuses.
- For replacement use fuses of same type and rating only.
- The operation of a class 3B laser show laser is only allowed if the show is controlled by a skilled and well-trained operator familiar with the data included in this manual.
- The user is responsible for correct positioning and operating of the Galactic Beam G40. The manufacturer will not accept liability for damages caused by the misuse or incorrect installation of this device.
- This device falls under protection class I. Therefore it is essential to connect the yellow/green conductor to earth.
- The laser will only work between 15-35°C.
- After 3 hours working, you must shut off the laser and let the laser diode cool off for 30 minutes, otherwise the laser could be damaged and the warranty becomes void.
- Repairs, servicing and electric connection must be carried out by a qualified technician.
- WARRANTY: Till one year after date of purchase.



**CAUTION! Eyedamages!!!**  
**Avoid looking directly into the lightsource!!!**  
**(meant especially for epileptics)!!!**



### Operating Determinations

- This device is not designed for permanent operation. Consistent operation breaks will ensure that the device will serve you for a long time without defects.
- The minimum distance between light-output and the illuminated surface must be more than 1 meter.
- The maximum ambient temperature  $t_a = 35^\circ\text{C}$  must never be exceeded.
- The relative humidity must not exceed 50 % with an ambient temperature of  $30^\circ\text{C}$ .
- If this device is operated in any other way, than the one described in this manual, the product may suffer damages and the warranty becomes void.
- Any other operation may lead to dangers like short-circuit, burns, electric shock, crash etc.

You endanger your own safety and the safety of others!

## Laser safety for a Class 3B Laser Product



CAUTION: AVOID EXPOSURE TO BEAM: Avoid direct eye contact with laser light. Never intentionally expose your eyes or others to direct laser radiation.

### Compliance Statement

Your Galactic Laser has been designed to comply with FDA and IEC Standards for its classification. The Galactic is a Class IIIB laser product.

### Laser Safety and Compliance Information

The Galactic is manufactured to comply with the IEC 60825-1 and in accordance with U.S. Food and Drug Administration (FDA) Standards Listed under FDA Document 21 CFR 1040 and subsequent laser notices.

### Product Classification and Manufacturing Label Identification

Laser Classification	Class IIIB
Cooling	TE Cooling
Laser medium	wavelength 532 nm / Green (DPSS Nd:YV04)
Output	>40mW Green
Beam Diameter	<18mm at aperture
Pulse Data All pulses	< 4Hz (>0.25sec)
Divergence (each beam)	<2 mrad
Divergence (total light)	<160 degrees

The legal requirements for using laser entertainment products vary from country to country. The user is responsible for the legal requirements at the location/country of use.

Further guidelines and safety programs for safe use of lasers can be found in the ANSI Z136.1 Standard "For Safe Use of Lasers", available from [www.laserinstitute.org](http://www.laserinstitute.org). Many local governments, corporations, agencies, military and others, require all lasers to be used under the guidelines of ANSI Z136.1. Laser Display guidance can be obtained via the International Laser Display Association, [www.laserist.org](http://www.laserist.org).

CAUTION: The use of corrective eye wear or optics for viewing at distances such as telescopes or binoculars within a distance of 100mm may pose an eye hazard.



This laser product is a Class IIIB laser and has an Interlocked housing.




There are no user serviceable parts inside. Tampering or removing warranty seals will void your products limited warranty.



Combo label with the Product Model Number, Serial Number, Date of Manufacturing, Laser Light Warning Label, Warranty Void Label and Interlocked Housing Label

Proper Usage Safety and Compliance Information



According to FDA Regulations you should operate this product as stated on the left.

### Rigging


Please follow the European and national guidelines concerning rigging, trussing and all other safety issues.

Do not attempt the installation yourself !

Always let the installation be carried out by an authorized dealer !

### Procedure:

- If the Galactic is lowered from the ceiling or high joists, professional trussing systems have to be used.
- Use a clamp to mount the Galactic, with the mounting-bracket, to the trussing system.
- The Galactic must never be fixed swinging freely in the room.
- The installation must always be secured with a safety attachment, e.g. an appropriate safety net or safety-cable.
- When rigging, derigging or servicing the Galactic, always make sure, that the area below the installation place is blocked and staying in the area is forbidden.




The Galactic can be placed on a flat stage floor or mounted to any kind of truss by a clamp.

Improper installation can cause serious damage to people and property !


## Connection with the mains

Connect the device to the mains with the power-plug.

Always pay attention, that the right color cable is connected to the right place.

International	EU Cable	UK Cable	US Cable	Pin
L	BROWN	RED	YELLOW/COPPER	FASE
N	BLUE	BLACK	SILVER	NULL
	YELLOW/GREEN	GREEN	GREEN	EARTH

Make sure that the device is always connected properly to the earth!



### Return Procedure



Returned merchandise must be sent prepaid and in the original packing, call tags will not be issued. Package must be clearly labeled with a Return Authorization Number (RMA number). Products returned without an RMA number will be refused. Highlite will not accept the returned goods or any responsibility. Call Highlite 0031-455667723 or mail [aftersales@highlite.nl](mailto:aftersales@highlite.nl) and request an RMA prior to shipping the fixture. Be prepared to provide the model number, serial number and a brief description of the cause for the return. Be sure to properly pack fixture, any shipping damage resulting from inadequate packaging is the customer's responsibility. Highlite reserves the right to use its own discretion to repair or replace product(s). As a suggestion, proper UPS packing or double-boxing is always a safe method to use.

**Note: If you are given an RMA number, please include the following information on a piece of paper inside the box:**

- 01) Your name
- 02) Your address
- 03) Your phone number
- 04) A brief description of the symptoms

## Claims

The client has the obligation to check the delivered goods immediately upon delivery for any shortcomings and/or visible defects, or perform this check after our announcement that the goods are at their disposal. Damage incurred in shipping is the responsibility of the shipper; therefore the damage must be reported to the carrier upon receipt of merchandise.

It is the customer's responsibility to notify and submit claims with the shipper in the event that a fixture is damaged due to shipping. Transportation damage has to be reported to us within one day after receipt of the delivery.

Any return shipment has to be made post-paid at all times. Return shipments must be accompanied with a letter defining the reason for return shipment. Non-prepaid return shipments will be refused, unless otherwise agreed in writing.

Complaints against us must be made known in writing or by fax within 10 working days after receipt of the invoice. After this period complaints will not be handled anymore.

Complaints will only then be considered if the client has so far complied with all parts of the agreement, regardless of the agreement of which the obligation is resulting.

## Description of the device

### Features

The Showtec Galactic Beam G40 is a laser effect with high output and great effects.

- 40mW Green Fatbeam Laser
- Strong solid beam
- By using fat-beam technology we are able to use 40mW laser and still be compliance to IEC-60825
- When using multiple units together, you can make a great and cost effective beam-show
- Power Input: AC 100-240V, 50/60Hz
- Power Consumption: 12 Watt
- Beam Diameter <18mm at aperture
- Laser Class: 3B
- Laser Modulation: TTL
- Laser Safety: EN/IEC 60825-1 Ed 2, 2007-03
- Laser Color: Green
- Laser Power: >40mW 532nm Green
- Scan Angle: +/-80°
- Control Modes: Auto, Sound, Master/Slave, DMX
- Divergence (each beam) <2 mrad; Divergence (total light) <160 degrees
- 3-pin DMX In and 3-pin DMX Out
- Clear LCD display for all settings
- Compact strong metal housing
- Music-controlled via built-in microphone
- 8 DMX Channels
- Safety Features: Key switch, Interlock
- Fuse 1L / 250V
- Dimensions: 300 x 88 x 222 mm (LxWxH)
- Weight: 2,3 Kg
- Accessories: 2 Keys, Interlock test connector

### Overview




Fig. 01

## Backside




Fig. 02

- 01) ON/OFF
- 02) Fuse 1 A/250V
- 03) IEC Powerconnector
- 04) Lock On/Off
- 05) 3-pin DMX signal connector (OUT)
- 06) 3-pin DMX signal connector (IN)
- 07) Remote Control
- 08) LCD Display + Menu Buttons
- 09) Cooling Fan
- 10) Built-in Microphone

NOTE: Knowledge of DMX is required to fully utilize this unit.

## Installation


Remove all packing materials from the Galactic. Check that all foam and plastic padding is removed. Connect all cables.

**Do not supply power before the whole system is set up and connected properly.**

**Always disconnect from electric mains power supply before cleaning or servicing.**

**Damages caused by non-observance are not subject to warranty.**

By using the screw hole(s) on the side and/or top of the fixture, the laser(s) can be installed in any desired position. Check below for some examples.



## Set Up and Operation


Follow the directions below, as they pertain to your preferred operation mode. Before plugging the unit in, always make sure that the power supply matches the product specification voltage. Do not attempt to operate a 120V specification product on 230V power, or vice versa. Connect the device to the main power supply. The device can be music-controlled by its built-in microphone.

The Interlock plug/remote plug and safety keys are included in the box. The interlock is the "included-in-the-box" successor for the optional remote interlock (51316)


 They should be kept with the Galactic laser !!! 

The following safety precautions should be followed:

- The interlock plug should be placed on the backside (7) of your Galactic laser.
- The keys should be put into the lock (4) of your Galactic laser.




 **Warning** 



### Exclusion of liability

Be aware that in some countries, there are additional regulations, regarding the use of laser devices. Therefore, we strongly advise you to verify your national laws with your authorities: We don't take any responsibility for eventual discrepancies, changes or adaptations regarding lawful use of laser devices.



## Control Modes

There are 4 modes:

- Auto run (visual effects)
- Sound-controlled
- Master/Slave
- DMX512

### One Galactic Auto run (visual effects)

- 01) Fasten the effect light onto firm trussing. Leave at least 0,5 meter on all sides for air circulation.
- 02) Always use a safety cable (ordercode 70140 / 70141).
- 03) Plug the end of the electric mains power cord into a proper electric power supply socket.
- 04) When the Galactic is not connected by a DMX-cable, it functions as a stand-alone device.
- 05) Please see page 17 for more information about the Auto run visual effects.

### One Galactic Sound-controlled

- 01) Fasten the effect light onto firm trussing. Leave at least 0,5 meter on all sides for air circulation.
- 02) Always use a safety cable (ordercode 70140 / 70141).
- 03) Plug the end of the electric mains power cord into a proper electric power supply socket.
- 04) When the Galactic is not connected by a DMX-cable, it functions as a stand-alone device.
- 05) Please see page 17+18 for more information about the about the sound-control options.

### Multiple Galactics (Master/Slave control)

- 01) Fasten the effect light onto firm trussing. Leave at least 0,5 meter on all sides for air circulation.
- 02) Always use a safety cable (ordercode 70140 / 70141).
- 03) Plug the end of the electric mains power cord into a proper electric power supply socket.
- 04) Use a 3-p XLR cable to connect the Galactic.

The pins:



1. Earth
2. Signal (-)
3. Signal (+)

- 05) Link the units as shown in (Fig. 03), Connect a DMX signal cable from the first unit's DMX "out" socket to the second unit's "in" socket. Repeat this process to link the second, third, and fourth units. You can use the same functions on the master device as described on page 17+18 (Autorun or Music control). This means on the master device you can set your desired operation Mode and all slave devices will react the same as the master device.

### Multiple Galactics (Master/Slave control)





Fig. 03


## Multiple Galactics (DMX Control)

- 01) Fasten the effect light onto firm trussing. Leave at least 0,5 meter on all sides for air circulation.
- 02) Always use a safety cable (ordercode 70140 / 70141).
- 03) Plug the end of the electric mains power cord into a proper electric power supply socket.
- 04) Use a 3-p XLR cable to connect the Galactics and other devices.



- 05) Link the units as shown in (figure 04), Connect a DMX signal cable from the first unit's DMX "out" socket to the second unit's "in" socket. Repeat this process to link the second, third, and fourth units.
- 06) Supply electric power: Plug electric mains power cords into each unit's IEC socket, then plug the other end of the mains power cord into proper electric power supply sockets, starting with the first unit. Do not supply power before the whole system is set up and connected properly. Design your show according to your DMX controller functions.

## Multiple Galactics DMX Set Up



Max. 30 Galactics

Fig. 04

**Note : Link all cables before connecting electric power**

### Fixture Linking

You will need a serial data link to run light shows of one or more fixtures using a DMX-512 controller or to run synchronized shows on two or more fixtures set to a master/slave operating mode. The combined number of channels required by all the fixtures on a serial data link determines the number of fixtures the data link can support.

**Important:** Fixtures on a serial data link must be daisy chained in one single line. To comply with the EIA-485 standard no more than 30 devices should be connected on one data link. Connecting more than 30 fixtures on one serial data link without the use of a DMX optically isolated splitter may result in deterioration of the digital DMX signal.



Maximum recommended DMX data link distance: 100 meters

Maximum recommended number of Galactics on a DMX data link: 30 fixtures

### Data Cabling


To link fixtures together you must obtain data cables. You can purchase DAP Audio certified DMX cables directly from a dealer/distributor or construct your own cable. If you choose to create your own cable please use data-grade cables that can carry a high quality signal and are less prone to electromagnetic interference.

#### DAP Audio DMX Data Cables

- DAP Audio Basic microphone cable for allround use. bal. XLR/M 3-pin > XLR/F 3-pin. **Ordercode** FL01150 (1,5 m), FL013 (3 m), FL016 (6 m), FL0110 (10 m), FL0115 (15 m), FL0120 (20 m).
- DAP Audio X-type data cable XLR/M 3-pin > XLR/F 3-pin. **Ordercode** FLX0175 (0,75 m), FLX01150 (1,5 m), FLX013 (3 m), FLX016 (6 m), FLX0110 (10 m).
- DAP Audio cable for the demanding user with exceptional audio-qualities and connector made by Neutrik®. **Ordercode** FL71150 (1,5 m), FL713 (3 m), FL716 (6 m), FL7110 (10 m).
- DAP Audio cable for the demanding user with exceptional audio-qualities and connector made by Neutrik®. **Ordercode** FL7275 (0,75 m), FL72150 (1,5 m), FL723 (3 m), FL726 (6 m), FL7210 (10 m).
- DAP Audio 110 Ohm cable with digital signal transmission. **Ordercode** FL0975 (0,75 m), FL09150 (1,5 m), FL093 (3 m), FL096 (6 m), FL0910 (10 m), FL0915 (15 m), FL0920 (20 m).

The Galactic can be operated with a controller in **control mode** or without the controller in **stand-alone mode**.

## Control Panel



- A) LED Display
- B) Func button
- C) Up Button
- D) Down Button
- E) Enter Button

Fig. 05

## Control Mode

The fixtures are individually addressed on a data-link and connected to the controller. The fixtures respond to the DMX signal from the controller. (When you select the DMX address and save it, the controller will display the saved DMX address the next time.)

## DMX Addressing

The control panel on the front side of the base allows you to assign the DMX fixture address, which is the first channel from which the Galactic will respond to the controller.

Please note when you use the controller, the unit has **8** channels.

When using multiple Galactics, make sure you set the DMX addresses right.

Therefore, the DMX address of the first Galactics should be **1(001)**; the DMX address of the second Galactic should be **1+8=9 (009)**; the DMX address of the third Galactic should be **9+8=17 (017)**, etc. Please, be sure that you don't have any overlapping channels in order to control each Galactic correctly.

If two or more Galactics are addressed similarly, they will work similarly.

## Controlling:

After having addressed all Galactic fixtures, you may now start operating these via your lighting controller.

**Note:** After switching on, the Galactic will automatically detect whether DMX 512 data is received or not. If there is no data received at the DMX-input, the "LED" on the control panel will not flash.

The problem may be:

- The XLR cable from the controller is not connected with the input of the Galactic.
- The controller is switched off or defective, the cable or connector is defective, or the signal wires are swapped in the input connector.

**Note:** It's necessary to insert a XLR termination plug (with 120 Ohm) in the last fixture in order to ensure proper transmission on the DMX data link.


### ⚠ Display Off after 30 seconds ⚠

When no button is pressed for 30 seconds, the display will turn off.

To light up the display, you have to press the FUNC button.



Once you have pressed the button, the display will light up.

Menu Overview



## Main Menu Options

<b>AUE</b>	Automatic Show with Patterns and Solid Beams
<b>AdF</b>	Automatic / Sound-active Moving Beams
<b>SoP</b>	Fixed Beam Sound-active to Block
<b>SoN</b>	Fixed Beam Sound-active to Beam
<b>S 0</b>	Sensitivity Mode
<b>001</b>	DMX address
<b>SLA</b>	Master/Slave Mode
<b>MPR</b>	Pattern Mirror Reverse
<b>SEt</b>	Default Setting

 You can only change a certain setting when the display is blinking.   
If you can't change a certain value, please press the Function-button once and then change the value.

### 1. Automatic / Sound-active Show

- 01) Press the **FUNC** button, until the display shows **AUE**.
- 02) Use the Up / Down buttons to scroll through the entire menu.

<b>AUE</b>	Automatic Show with Patterns and Solid Beams
<b>SoU</b>	Sound Activated Show with Patterns and Solid Beams

- 03) Use the **ENTER** button to store your setting.

### 2. Automatic / Sound-active Patterns

- 01) Press the **FUNC** button, until the display shows **AdF**.
- 02) Use the Up / Down buttons to scroll through the entire menu.


<b>AdF</b>	Automatic Show with moving Solid Beams ( <b>Fast</b> )
<b>AdS</b>	Automatic Show with moving Solid Beams ( <b>Slow</b> )
<b>Sdr</b>	Sound Activated Show with random moving Solid Beams

- 03) Use the **ENTER** button to store your setting.





### 3. Sound-active to Beam ON

- 01) Press the **FUNC** button, until the display shows **SoP**.
- 02) The Galactic Beam is now sound activated to Beam ON.

#### 4. Sound-active to Beam OFF

- 01) Press the **FUNC** button, until the display shows .
- 02) The Galactic Beam is now sound activated to Beam OFF.

#### 5. Sensitivity Mode

- 01) Press the **FUNC** button, until the display shows .
- 02) You can choose 10 different Audio Sensitivity levels.
- 03) Use the Up / Down buttons to select the required address from   .







No audio activation




Audio sensitivity, from low to highly sensitive.

- 04) Use the **ENTER** button to store your setting.


#### 6. DMX Mode

- 01) Press the **FUNC** button, until the display shows .
- 02) You can choose 505 different DMX addresses.
- 03) Use the Up / Down buttons to select the required address from   .
- 04) Use the **ENTER** button to store your setting.

#### 7. Slave Mode

- 01) Press the **FUNC** button, until the display shows .
- 02) You can use the same functions on the master device as described on page 12.  
This means, you can set your desired operation Mode on the master device and all slave devices will react the same as the master device.
- 03) Use the **ENTER** button to store your setting.

#### 8. Reverse Setting

- 01) Press the **FUNC** button, until the display shows .
- 02) Use the Up / Down buttons to select:




Vertical Reverse Setting (x-axis reverse)



Horizontal Reverse Setting (y-axis reverse)

- 03) Use the **ENTER** button to store your setting.

#### 9. Factory default setting

- 01) Press the **FUNC** button, until the display shows .
- 02) Use the Up / Down buttons to select:



Default Horizontal Setting



Default Vertical Setting

- 03) Switch between both settings, by pressing the Up / Down buttons.
- 04) Use the **ENTER** button to store your setting.

## DMX Channels

## 8 Channels

## Channel 1 – Built-in Programs

0-31	Laser OFF
32-63	<b>AdS</b> (Auto show with slow solid beam effect)
64-95	<b>AdF</b> (Auto show with fast solid beam effect)
96-127	<b>Sdr</b> (Sound activated random solid beam)
128-159	<b>AUT</b> (Automatic Show with Patterns and Solid Beams)
160-191	<b>SOU</b> (Sound activated Show with Patterns and Solid Beams)
192-223	<b>DMX</b> (Solid Beam Mode)
224-255	<b>DMX</b> (Pattern Beam Mode)



Only when CH1 is set between 221-255, CH2-CH8 will function.



## Channel 2 – 32 Patterns

1-255 32 Individual patterns

## Channel 3 – Zoom

0-127	Zoom from 100% – 5%
128-169	Zoom In from 100% – 5% (slow to fast)
170-209	Zoom Out from 5% - 100% (slow to fast)
210-255	Zoom In and Out from slow to fast



## Channel 4 – Y-axis Rolling

0-127	0-359 degree fixed Y Axis rolling
128-191	Clockwise rolling from slow to fast
192-255	Counterclockwise rolling from slow to fast



## Channel 5 – X-axis Rolling

0-127	0-359 degree fixed X Axis rolling
128-191	Clockwise rolling from slow to fast
192-255	Counterclockwise rolling from slow to fast



## Channel 6 – Z-axis Rolling

0-127	0-359 degree fixed Z Axis rolling
128-191	Clockwise rolling from slow to fast
192-255	Counterclockwise rolling from slow to fast



## Channel 7 – X-axis Moving

0-127	0-359 degree fixed Z Axis rolling
128-191	Clockwise rolling from slow to fast
192-255	Counterclockwise rolling from slow to fast



































## Channel 8 – Y-axis Moving

0-127	0-359 degree fixed Z Axis rolling
128-191	Clockwise rolling from slow to fast
192-255	Counterclockwise rolling from slow to fast



## Patterns

000-007		064-071		128-135		192-199	
008-015		072-079		136-143		200-207	
016-023		080-087		144-151		208-215	
024-031		088-095		152-159		216-223	
032-039		096-103		160-167		224-231	
040-047		104-111		168-175		232-239	
048-055		112-119		176-183		240-247	
056-063		120-127		184-191		248-255	

### Maintenance

---

The Showtec Galactic requires almost no maintenance. However, you should keep the unit clean. Otherwise, the fixture's light-output will be significantly reduced. Disconnect the mains power supply and then wipe the cover with a damp cloth. Wipe the front glass panel clean with glass cleaner and a soft cloth. Do not use alcohol or solvents. The front glass panel will require weekly cleaning, as smoke-fluid tends to build up residues, reducing the light-output very quickly. Do not immerse in liquid. Keep connections clean. Disconnect electric power, and then wipe the DMX and audio connections with a damp cloth. Make sure connections are thoroughly dry before linking equipment or supplying electric power.

The operator has to make sure that safety-relating and machine-technical installations are to be inspected by an expert after every year in the course of an acceptance test. The operator has to make sure that safety-relating and machine-technical installations are to be inspected by a skilled person once a year.

The following points have to be considered during the inspection:

- 01) All screws used for installing the device or parts of the device have to be tightly connected and must not be corroded.
- 02) There may not be any deformations on housings, fixations and installation spots.
- 03) Mechanically moving parts like axles, eyes and others may not show any traces of wearing.
- 04) The electric power supply cables must not show any damages or material fatigue.

### Replacing a Fuse

Power surges, short-circuit or inappropriate electrical power supply may cause a fuse to burn out. If the fuse burns out, the product will not function whatsoever. If this happens, follow the directions below to do so.

- 01) Unplug the unit from electric power source.
- 02) Insert a screwdriver into the slot in the fuse cover. Gently pry up the fuse cover. The fuse will come out.
- 03) Remove the used fuse. If brown or unclear, it is burned out.
- 04) Insert the replacement fuse into the holder where the old fuse was. Reinsert the fuse cover. Be sure to use a fuse of the same type and specification. See the product specification label for details.

## Troubleshooting

---

### No Light

This troubleshooting guide is meant to help solve simple problems.

If a problem occurs, carry out the steps below in sequence until a solution is found. Once the unit operates properly, do not carry out following steps.

If the light effect does not operate properly, refer servicing to a technician.

Response: Suspect three potential problem areas as: the power supply, the laser, the fuse.

- 01) Power supply. Check that the unit is plugged into an appropriate power supply.
- 02) The laser. Return the Galactic to your Showtec dealer.
- 03) The fuse. Replace the fuse. See page 21 for replacing the fuse.
- 04) If all of the above appears to be O.K., plug the unit in again.
- 05) If you are unable to determine the cause of the problem, do not open the Galactic, as this may damage the unit and the warranty will become void.
- 06) Return the device to your Showtec dealer.

### No Response to DMX

Response: Suspect the DMX cable or connectors, a controller malfunction, a light effect DMX card malfunction.

- 01) Check the DMX setting. Make sure that DMX addresses are correct.
- 02) Check the DMX polarity.
- 03) Check the DMX cable: Unplug the unit; change the DMX cable; then reconnect to electrical power. Try your DMX control again.
- 04) If you have intermittent DMX signal problems, check the pins on connectors of the fixture or the previous one
- 05) Determine whether the controller or light effect is at fault. Does the controller operate properly with other DMX products ? If not, take the controller in for repair. If so, take the DMX cable and the light effect to a qualified technician.
- 06) Check to see if the DMX cables run near or run alongside to high voltage cables that may cause damage or interference to DMX interface circuit.

### The fixture is powered on, but no laser coming out from aperture

- 01) Check the glass aperture cover on the front side. Smoke-fluid tends to build up residues, reducing the light-output very quickly.
- 02) Check whether the key switch (**4**) is set to ON.
- 03) Check whether the interlock plug (**7**) is connected.
- 04) Allow at least 30 minutes to warm up, when operating in low temperatures.
- 05) Check whether the device is in Sound mode, but no sound signal is present.
- 06) Check whether the device is in Slave mode.
- 07) Check whether the device is in DMX mode, but no DMX signal is present.

### The laser effect power is very weak

- 01) Allow at least 30 minutes to warm up, when operating in low temperatures.
- 02) Clean the scanner mirror with alcohol.
- 03) Clean the aperture glass on the front side with alcohol.

### The laser is on, but the pattern is not moving

- 01) Check whether the device is in Sound mode but the microphone is not detecting any sound signals.
- 02) Change the setting of the laser to a stand-alone program. Does the laser work ?
- 03) Try to control the fixture in DMX mode. Does the laser work ?

See next page for more problem solving.

Problem	Probable cause(s)	Remedy
One or more fixtures are completely dead.	No power to the fixture.	<ul style="list-style-type: none"> <li>• Check that power is switched on and cables are plugged in.</li> </ul>
	Primary fuse blown.	<ul style="list-style-type: none"> <li>• Replace fuse.</li> </ul>
Fixtures reset correctly, but all respond erratically or not at all to the controller.	The controller is not connected.	<ul style="list-style-type: none"> <li>• Connect controller.</li> </ul>
	3-pin XLR Out of the controller does not match XLR Out of the first fixture on the link (i.e. signal is reversed).	<ul style="list-style-type: none"> <li>• Install a phase reversing cable between the controller and the first fixture on the link.</li> </ul>
Fixtures reset correctly, but some respond erratically or not at all to the controller.	Poor data quality	<ul style="list-style-type: none"> <li>• Check data quality. If much lower than 100 percent, the problem may be a bad data link connection, poor quality or broken cables, missing termination plug, or a defective fixture disturbing the link.</li> </ul>
	Bad data link connection	<ul style="list-style-type: none"> <li>• Inspect connections and cables. Correct poor connections. Repair or replace damaged cables.</li> </ul>
	Data link not terminated with 120 Ohm termination plug.	<ul style="list-style-type: none"> <li>• Insert termination plug in output jack of the last fixture on the link.</li> </ul>
	Incorrect addressing of the fixtures.	<ul style="list-style-type: none"> <li>• Check address setting.</li> </ul>
	One of the fixtures is defective and disturbs data transmission on the link.	<ul style="list-style-type: none"> <li>• Bypass one fixture at a time until normal operation is regained: unplug both connectors and connect them directly together.</li> <li>• Have the defective fixture serviced by a qualified technician.</li> </ul>
	3-pin XLR Out on the fixtures does not match (pins 2 and 3 reversed).	<ul style="list-style-type: none"> <li>• Install a phase-reversing cable between the fixtures or swap pin 2 and 3 in the fixture, that behaves erratically.</li> </ul>
Shutter closes suddenly	The laser diode has lost its index position and the fixture is resetting the effect.	<ul style="list-style-type: none"> <li>• Contact a technician for servicing the problem persists.</li> </ul>
No light or laser cuts out intermittently	Fixture is too hot.	<ul style="list-style-type: none"> <li>• Allow fixture to cool.</li> <li>• Make sure air vents at control panel and front lens are not blocked.</li> <li>• Turn up the air conditioning .</li> </ul>
	Laser damaged	<ul style="list-style-type: none"> <li>• Disconnect fixture and return to your dealer.</li> </ul>
	The power supply settings do not match local AC voltage and frequency.	<ul style="list-style-type: none"> <li>• Disconnect fixture. Check settings and correct if necessary.</li> </ul>

## Product Specification

Model:	Showtec Galactic Beam G40
Input Voltage:	AC 100-240V, 50/60Hz
Continuous Power:	123W
Fuse	1L / 250V
Dimensions:	300 x 88 x 222 mm (LxWxH)
Weight:	2,3 Kg
<b>Operation and Programming</b>	
Signal pin OUT:	pin 1 earth, pin 2 (-), pin 3 (+)
Set Up and Addressing:	Clear LCD display for all settings
DMX Channels:	8
Signal input:	3-pin XLR male
Signal output:	3-pin XLR female
<b>Electro-mechanical effects</b>	
<ul style="list-style-type: none"> <li>• DMX-control via standard DMX-controller</li> <li>• By using fat-beam technology we are able to use 300mW laser and still be compliance to IEC-60825</li> <li>• When using multiple units together, you can make a great and cost effective beam-show</li> <li>• Beam Diameter &lt;18mm at aperture</li> <li>• Laser Class: 3B</li> <li>• Laser Modulation: TTL</li> <li>• Laser Safety: EN/IEC 60825-1 Ed 2, 2007-03</li> <li>• Laser Color: Green</li> <li>• Laser Power: &gt;40mW 532nm Blue</li> <li>• Scan Angle: +/-80°</li> <li>• Control Modes: Auto, Sound, Master/Slave, DMX</li> <li>• Divergence (each beam) &lt;2 mrad; Divergence (total light) &lt;160 degrees</li> <li>• Compact strong metal housing</li> <li>• Music-controlled via built-in microphone</li> <li>• Safety Features: Key switch, Interlock</li> <li>• Accessories: 2 Keys, Interlock test connector</li> </ul>	
Max. ambient temperature $t_a$ :	35°C; Max. housing temperature $t_B$ : 80°C
<b>Minimum distance:</b>	
Minimum distance from flammable surfaces:	0.5m
Minimum distance to lighted object:	1m


Design and product specifications are subject to change without prior notice.



Website: [www.Showtec.info](http://www.Showtec.info)

Email: [service@highlite.nl](mailto:service@highlite.nl)

## Dimensions







©2015 Showtec